




PROLINK












We provide our customers with exceptional PRODUCTS in accordance with the highest international standards and also provide SERVICES that meets our customers' needs or exceeds their expectations.

Powered by: **PROLINK**

Description

Prolink Media Converter 10/100M base-TX/FX MM, 20k

Features

-  **10/100Mbps Copper to 100Mbps Fiber**
-  **Full wire speed conversion**
-  **Auto-negotiation, auto MDI/MDI-X detection**
-  **Link fault pass through function**
-  **Far End Fault function**
-  **Stand-alone or chassis installation in MCC-14R**
-  **Optional DIN rail mounting**
-  **Low power consumption**
-  **Wide range of fiber options**



Specifications

Standards	IEEE 802.3, 802.3u
Copper Port (TP)	Shielded RJ-45 jack Cat5 UTP cable up to 100m Auto-negotiation for speed and duplex Forced mode with speed and duplex settings Speed for 10Mbps or 100Mbps, Full-duplex or Half-duplex support
Fiber Port (FX)	Forced 100Mbps, Full-duplex (factory default) Far end fault detection Multi-Mode: 50/125 and Single Mode: 9/125
LEDs	Power Status Link/Activity Speed Duplex
Power Input	+5VDC
Environment	Operating Temperature: -5° C ~ 55° C Storage Temperature: -20° C ~ 70° C Humidity: 5% ~ 90% non-condensing
Dimensions	3.70 x 2.79 x 1.02 inches (94 x 71 x 26 mm)